



## L42W665

ENVISION *Series*

<b>Feature</b>	<b>42" Widescreen LCD TV</b> <b>Wide XGA (1366x 768) Resolution</b> <b>High Brightness (500 cd/m<sup>2</sup>)</b> <b>High Contrast Ratio (1200:1)</b> <b>Wide Viewing Angle (178 H / 178 V)</b> <b>Analog TV: NTSC Built-in 181 channel Tuner with MTS, SAP, Closed Caption &amp; V-chip</b> <b>Digital TV: ATSC 8-VSB, Clear-QAM</b>		
<b>Items</b>	<b>Specification</b>		
<b>LCD Panel</b>	Screen Size	42" TFT-LCD Panel	
	Aspect Ratio	16:9	
	Resolution	1366 × 768 (WXGA)	
	Display Area (opening) H x V	930.25mm × 523.01mm	
	Pixel Pitch	0.681mm × 0.681mm	
	Display colors	16.7 million	
	Contrast Ratio	1200:1	
	Brightness	500cd / m <sup>2</sup>	
Viewing Angle	178° (Horizontal) / 178° (Vertical)		
<b>Digital TV</b>	Video System	ATSC 8-VSB, MP@HL/MP@ML, Clear-QAM	
	Sound System	Dolby/PCM/MPEG(Layer I & II)	
<b>Analog TV</b>	Video System	NTSC 181 Channel with Electronic PLL Tuner	
	Sound System	MTS + SAP	
<b>Analog Video</b>	AV1/AV2	Composite Video × 1	Audio L/R × 1 (Share)
		S-Video × 1	
	AV3/AV4	Composite Video × 1 S-Video × 1	Audio L/R × 1 (Share)
	AV5/AV6	YPbPr × 2	Audio L/R × 2
<b>Digital Video</b>	HDMI	HDMI × 2	
<b>PC Input</b>	Signal Input	D-Sub	
	PnP compatibility	DDC2B	
	Input frequency	FH: 31.5KHz to 60 KHz FV: 56Hz to 75Hz	
	Recommended	1360 x 768 (60Hz)	
	Input Audio	Mini-jack for stereo (3.5ø)	
<b>Audio Output</b>	Audio Output: L / R	Speaker (built-in): 8W + 8W	
		Headphone Mini-jack for stereo (3.5ø)	
	Digital Output	S/PDIF x 1 (RCA Jack)	
<b>OSD language</b>	English/Spanish/French		
<b>Table Stand</b>	Included		
<b>Wall Mount</b>	VESA		
<b>Power</b>	Power Supply	AC100V~240V, 50/60Hz	
	Power Consumption	TBD	
<b>Dimension</b>	W x H x D (with stand)	TBD	
<b>Weight (Net)</b>	Kg (w/o Accessories)	TBD	
<b>Accessories</b>	Remote controller, Batteries (x2), AC Power cord, Users manual		
<b>UPC Code</b>	685417014583		